

HTA-700B v.2 tubes upgrade

TAGA Harmony recommends that the below actions and modifications are performed by the authorized service only.

1. Switch off the unit and disconnect the power cord;
2. Disconnect all connected devices and speakers;
3. Place the amplifier upside down on the flat surface;
4. Unscrew screws located on the bottom of the amplifier and remove the bottom cover;
5. There are two 3-pin jumper blocks located on the main board (marked 6N2 12AX7);
6. Remove the jumper shunt in each block and place it in the position marked 12AX7;
7. Screw in the bottom cover;
8. Exchange tubes to 12AX7 type;
9. Your amplifier is ready for operation.



CAUTION

RISK OF ELECTRIC SHOCK

